

ADDRESSABLE MANUAL PULL STATION



S-A4061

DESCRIPTION

The Addressable Manual Pull Station is dual action and features translucent plastic at the center, allowing visibility of an internal LED that indicates alarm condition and polling status. The unit is addressable using a DIP switch protected within the pull station. The Manual Pull Station may be flush mounted on a single gang work or use an optional back cover.

INSTALLATION

Product will mount semi-flush into a single-gang electrical outlet box, or will surface mount to the Surface Back Box.

Pushing in, then pulling down on the handle causes it to latch in the down/activated position.

Once latched, the activated lag (in bright yellow) appears at the bottom of the station face. To reset the station, simply unlock the station with the key and allow the door to open. This action resets the handle; closing the door automatically resets the switch.

Each manual pull station, on command from the control panel, sends data to the panel representing the state of the manual switch. The priority interrupt addressing (1-126) is set via the enclosed 7 segment DIP switch.

FEATURES

- Control Panel Compatibility.
- Key lock.
- Easily resettable.
- LED visible even when Pull Station is closed.

TECHNICAL DATA

Operating Voltage	17 - 28 V DC
Current Consumption at 24 V	
Stand by current	200 μ A
LED Operated Alarm current	3.6 mA + Quiescent
Installation Temperature	0°C to 60°C
Operating Temperature	0°C to 38°C
UL Listed Voltage	20-28 V DC
Dimension	
Pull station	108 mm x 140 mm x 28 mm
Surface Backbox	108 mm x 140 mm x 45 mm
Weight	
Pull station	200 g
Surface Backbox	327 g
IP Rating	25

ORDERING INFORMATION

Part number	Product Description
S-A4061	Manual Pull Station
S-A4062	Back Box For Manual Pull Station

MOUNTING DIAGRAM

